

Maha Energy Corp.
545-C W. Lambert Rd. Brea, CA 92821
Tel: 1-800-376-9992 -or- (714) 990-4557 Fax: (714) 990-1325



Point your browser at: <http://www.maha-comm.com>
Internet E-mail: tech@maha-comm.com

MAHA

*"Your Supplier, Your Partner,
Your Friend!"*

Product Technical Data Sheet

Maha Part Number	MH-C204F
UPC Number	802366-12201-9
Product Description	Intelligent 4 AA / AAA NiMH & NiCD battery charger
Rapid Charge Current:	500mA +/- 10%
Trickle Charge Current:	24mA +/- 10%
Discharge Rate:	200mA +/- 50mA
Charging Cell Configuration:	Two or Four AA / AAA NiCD or NiMH
Microprocessor:	Two independent circuits, capable of simultaneous charge and discharge. OdeltaV, peak voltage based.
Output Voltage (without load)	1.5V
Peak Voltage Value:	1.39V
Power Supply Voltage:	12VDC (Range: 10V-16V)
Power Consumption:	500mA; Adapter included.
Adapter	12V 500mA AC-to-DC Class 2 Transformer

DOCUMENT CONTROL
VERSION: V. 1.00
DATE PRINTED: 11/23/00

Maha reserves the right to change any specifications listed in this data sheet without notice.